

G30

Manual Clamping Gyroscopic Mixer



➡ Robust and Reliable

➡ Easy Maintenance

SANTINT • CHINA

Add: Sangong & Xingyun Road,
Xingyang City, Zhengzhou City,
Henan Province, 450121 China
Email: info@santint.com

SANTINT • HOLLAND

Add: Gieterij 28, 2211 XK
Noordwijkerhout, The Netherlands
Email: sales@santint-europe.com

SANTINT • POLAND

Add: 43 Szyszkowa Street,
02-285 Warsaw, Poland
Email: albert@santintpoland.com

SANTINT • U.S.A

Add: 2000 Bloomingdale Road,
Suite 205, Glendale Heights,
IL 60139, U.S.A
Email: info@santintusa.com

SANTINT • BRAZIL

Add: Av. Rosa Kasinski, 1109,
G11 e 12 Capuava, Mauá,
SP - Brasil CEP 09380-128
Email: marcos@santint.com

SANTINT • INDIA

Add: H.No.692, Gala No.04, Print
World Industrial Complex,
Bhatale, Vehele Village, Opposite
Balaji Compound, Bhiwandi,
Maharashtra - 421302
Email: nick@santint.com

G30 FEATURES >>>

SANTINT
WHERE INNOVATION MEETS PRECISION




- 1 3 Mixing Speeds**
Different speeds to suit various can sizes.




- 2 Robust and Reliable**
Simple structure, heavy loading.

- 3 Safety Lock**



- 4 Easy Maintenance**

- 5 Simple Inner Structure**



- Motor Power: 0.75kW
- Power Supply: 220/110V 50/60Hz
- Plate Moving Range: 75~430mm
- Mixing Speed: 110/130/150rpm

- Can Weight: 35kg
- Can Size: Diameter 50~300mm Height 80~420mm
- Mixing Range: 1~20L

- Mixing Time: 4 Mins for square Can 3 Mins for big can 2 Mins for small can
- Machine Dimension(WxDxH): 855x715x1040mm
- Packing Dimension(WxDxH): 910x790x1165mm 26 Pieces/20GP

- Net Weight: 155kg
- Noise: <70dB

G30

Technical Parameters

